


3 Oscilloscope

The submenu "Oscilloscope" contains the two additional menu items "Show" and "Configure".


Monitor

Using the menu key "Monitor", open first the submenu "Diagnosis" and then the menu "Oscilloscope". The following submenu is displayed:



3.1 "Show" function

Saved traces can be viewed and analyzed with this function.



A window is opened on the display. All of the files which are saved in the directory C: \PROGRAM FILES\KRC\TRACE and which have the extension TRC are displayed here.



3.1.1 File selection

The desired file can be selected using the arrow keys. The name of the selected file will be indicated by a color background. Move the cursor to a file having the end digit 1. It contains data from the digital servoelectronics DSE.


Ok

After selecting this file, please press the softkey "Ok".

A new window is opened.

3.1.2 The oscilloscope display

The contents of your screen should now look similar to those below. However, you have probably recorded other data with a different configuration. For this reason, the individual curves also have different forms and different colors on your screen.




More detailed information about the curves can be found in the upper part of the display. The color, the assigned variable, the unit of measurement and the scale of the display are listed in sequence for each curve.

The left bar (vertical) shows values which, when multiplied by the scale of the display, represent the value of a curve at a point in time that is shown below on the time axis (horizontal).

If signals from the controller's inputs and outputs are displayed, the left bar (vertical) also contains numbers as placeholders for the number of the selected inputs or outputs.



Inputs or outputs are only displayed while they have the value "TRUE" (as long as an input or output has the value "FALSE", you will only see a broken gray line).



The "active" color is permanently displayed at the bottom left of the screen.

You can "move" through the entire trace by using the arrow keys.

Close

You can exit the display function again at any time by pressing the softkey "Close".

3.1.3 The information window

Info

Now first press the softkey "Info". A window is opened displaying further information about the individual curves. The information window appears as follows for the example given above:

No.	File	Channel	Name	Color	Visible
Graph 0	C:\PROGRAMME\KRC\Trace\g...	Channel 0	\$IN[1..16]	Blue	yes
Graph 1	C:\PROGRAMME\KRC\Trace\g...	Channel 1	\$IN[17..32]	Green	yes
Graph 2	C:\PROGRAMME\KRC\Trace\g...	Channel 2	\$OUT[1..16]	White	yes
Graph 3	C:\PROGRAMME\KRC\Trace\g...	Channel 3	\$OUT[17..32]	Red	yes

The color and the number of each curve are displayed in the first column.

The second column specifies the file from which the data for the curve have been read.

You can see the channel to which the curve has been assigned and the variable that it represents in the columns "Channel" and "Name".

The name of the color of the curve is displayed in the column "Color".

The last column indicates whether the curve is displayed or not.

Info

Now press the softkey "Info" again. The window is closed. You can switch between the two functions by using this softkey.

3.1.4 The softkey bar

Let us now turn to the softkey bar. It has four levels in the function "Show".

===>

You can switch between these four levels by using the softkey "===>".

Blue	Green	White	Red	Info	--->	Close
Magenta	Brown	Yellow	Cyan	Info	--->	Close
Zoom	Unzoom	Channel	RMS	Print	--->	Close
VCursor 1	VCursor 2	HCursor 1	HCursor 2	Filter on/off	--->	Close

3.1.5 The color softkeys

To make it as easy as possible to read the display, a maximum of eight different colors (blue, green, white, red, magenta, brown, yellow and cyan) are shown.

Blue	Green	White	Red	Info	--->	Close
Magenta	Brown	Yellow	Cyan	Info	--->	Close

Curves can be displayed or removed on the basis of their colors with the aid of the color softkeys. This is done quite simply by pressing the appropriate color softkey.

Blue

Please remove the blue curve by pressing the softkey "Blue" once. Then open the information window. Reminder: To do so, press the softkey "Info".

Number	File	Channel	Description	Color	Visible
Graph 0	C:\PROGRAMME\KRC\Trace\g...	Channel 0	\$IN[1..16]	Blue	No
Graph 1	C:\PROGRAMME\KRC\Trace\g...	Channel 1	\$IN[17..32]	Green	Yes
Graph 2	C:\PROGRAMME\KRC\Trace\g...	Channel 2	\$OUT[1..16]	White	Yes
Graph 3	C:\PROGRAMME\KRC\Trace\g...	Channel 3	\$OUT[17..32]	Red	Yes

Your action has been registered in the last column (far right). "Visible" now has the value "No" for the blue curve.

Now close the information window again and then make the blue curve visible once more. To do so, press the color softkey "Blue" again.



If you press color softkeys while the information window is open, color assignments will be cancelled. The procedure for recovering cancelled color assignments is described in Section 3.6.

Certain graphs can also be removed by selecting the desired graph in the information window and pressing the "Enter" key. More detailed information on this can be found in Section 3.7.

3.1.6 The zoom function

Press the softkey "====>" repeatedly until the zoom functions appear in the softkey bar.



Zoom

When the softkey "Zoom" is pressed, a white cross about five millimeters high appears in the middle of the window. This can be moved about the entire window using the arrow keys. Move it to the position of your choice and then press the Enter key. The point that is currently selected represents a corner point of the zoom window, which must now be expanded using the arrow keys. Include everything that you want enlarged in this zoom window and then press the Enter key again. The contents of the zoom window will then be enlarged on the display.

Unzoom

To undo zooming, please press the softkey "Unzoom".

3.1.7 The scaling function

In the display, you are able to increase or reduce the amplitude of individual curves.

Channel

To do so, press the softkey "Channel" until the color of the desired curve is active. The active color is permanently displayed at the bottom left of the window.




Now observe what changes occur when you press the keys "M" or "N" in the ASCII alphabetic keypad.

N Pressing the key "N" in the ASCII alphabetic keypad gradually increases the amplitude.

M Pressing the key "M" in the ASCII alphabetic keypad gradually decreases the amplitude.

By using this function, it is also possible to clearly display curves which only have a small deflection or which are hidden by other curves.

The current scale is given in the top area of the display.




3.1.8 The r.m.s. value function

In order to determine the value that a curve represents during a certain period of time as easily as possible, the r.m.s. value function has been integrated.


Channel

To determine the r.m.s. value, you must press the softkey "Channel" to select the color used by the curve that is to be evaluated. The active color is permanently displayed at the bottom left of the window.




RMS

Then press the softkey "RMS". A vertical white line with the label "Evaluation of RMS" is displayed in the window.




Now move this line to the start point of your r.m.s. value evaluation using the "←" and "→" arrow keys and then press the Enter key.

You can now use the "←" and "→" arrow keys to define a sort of "measuring range", which is displayed as a white box.



After pressing the Enter key, the result of the evaluation is displayed in the window.



Should the text that is displayed be hidden by other curves and thus cannot be read, simply remove the other curves for the time being. Reminder: To do so, use the color softkeys.



To end the function "RMS", please press the softkey "RMS" again.



If you press the softkey "Close" instead, the entire display function will be ended.

3.2 Printing



If you would like to print out the contents of the screen, please press the softkey "Print".



The screen is printed on the current default printer of the operating system. The printer should be set to "Landscape".

3.3 The cursor functions


Press the softkey "===>" repeatedly until the cursor functions appear in the softkey bar.



You are able to place two vertical and two horizontal lines (cursors) inside the window with these functions. This enables you to determine the value that a curve represented at a certain time quite easily.


Channel

Press the softkey "Channel" until the color of the desired curve is active. The active color is permanently displayed at the bottom left of the window.




VCursor 1

If you then press the softkey "VCursor1", a vertical white line (cursor) is displayed in the window.




The value that the selected curve had at the time where the cursor is currently positioned is displayed at the top left of the window. When inputs or outputs are displayed, the bit pattern of the selected input or output group is shown here.



Now move the cursor using the arrow keys and observe how the top left of the display changes.

VCursor 2

Press the softkey "VCursor2". A second vertical white line (cursor) is displayed in the window.



The values for the second cursor now appear to the right of the display for the first cursor. When inputs or outputs are displayed, the bit pattern of the selected input or output group is also shown here. The time difference between these two cursors is displayed on the left-hand side.


These cursors can be removed again by pressing the softkey "VCursor1" or "VCursor2" once more.

HCursor 1

If the softkey "HCursor1" is pressed, a horizontal white line with the label "Function value cursor" will be displayed in the window.



When inputs and outputs are displayed, the function "HCursor" is not suitable for showing the numbers.




The value where the cursor is currently positioned is displayed at the top left of the window. Now move the cursor using the arrow keys and observe how the top left of the display changes.

HCursor 2

Press the softkey "HCursor2". A second horizontal white line is displayed in the window.



When inputs and outputs are displayed, the function "HCursor" is not suitable for showing the numbers.




The values for the second cursor now appear to the right of the display for the first cursor. The time difference between these two cursors is displayed on the lefthand side.

These lines can be removed again by pressing the softkeys "HCursor1" or "HCursor2" once more.


3.4 The filter function

Filter on/off

By pressing this softkey, you can switch on a software filter which "smooths" the displayed curves. This filter is switched off again by pressing this softkey once more.



unfiltered




filtered


3.5 Superposing traces

To allow you to compare data from different traces with each other, the function "TraceFile2" has been integrated.

To use this function, please open the menu by means of the menu key "Monitor". Then select "Diagnosis". The following display appears:



As you want to use the oscilloscope function "Show" to view traces that have already been saved, please confirm the offered selection "Oscilloscope". A further menu is opened, in which you also confirm the offered selection "Show" again.



A window is opened on the display. All of the files which are saved in the directory C: \PROGRAM FILES\KRC\TRACE and which have the extension TRC are displayed here.



The desired file can be selected using the arrow keys. The name of the selected file will be indicated by a color background. Move the cursor to a file with, for example, the end digit 3. Data from the controller's inputs and outputs are recorded in this file.

TraceFile 2


After selecting this file, please press the softkey "TraceFile2".

Now use the arrow keys to move the cursor to a file with the end digit 1, for example. DSE data are recorded in this file.

Ok

After selecting this file, please now press the softkey "Ok".

In the window, you can now see that the contents of these two traces are superposed on each other.



3.6 Changing color assignments

Info

The color assignments of the individual curves can be changed at any time. To do so, open the information window by pressing the softkey "Info".

No.	File	Channel	Name	Color	Visible
Graph 0	C:\PROGRAMME\KRC\Trace\g...	Channel 0	\$IN[1..16]	Blue	yes
Graph 1	C:\PROGRAMME\KRC\Trace\g...	Channel 1	\$IN[17..32]	Green	yes
Graph 2	C:\PROGRAMME\KRC\Trace\g...	Channel 2	\$OUT[1..16]	White	yes
Graph 3	C:\PROGRAMME\KRC\Trace\g...	Channel 3	\$OUT[17..32]	Red	yes

As an example, we now want to interchange the color assignments of curves 1 (currently still blue) and 3 (currently still red).

Blue

Press the color softkey "Blue" to deactivate the assignment that is valid for the curve.

Move the highlight to the curve with the number 3.

Blue

Press the color softkey "Blue" again to assign the color blue (which has just become available) to curve 3.

Move the highlight to curve 1, which is currently not assigned a color.

Red

Press the color softkey "Red" here to assign the color red to this curve.

Info

Now close the information window again.

3.7 Switching curves on and off

Info

It can sometimes be necessary to completely remove individual curves from the display. To do so, open the information window by pressing the softkey "Info".

No.	File	Channel	Name	Color	Visible
Graph 0	C:\PROGRAMME\KRC\Trace\g...	Channel 0	\$IN[1..16]	Blue	yes
Graph 1	C:\PROGRAMME\KRC\Trace\g...	Channel 1	\$IN[17..32]	Green	yes
Graph 2	C:\PROGRAMME\KRC\Trace\g...	Channel 2	\$OUT[1..16]	White	yes
Graph 3	C:\PROGRAMME\KRC\Trace\g...	Channel 3	\$OUT[17..32]	Red	yes

Select the curve that you would like to remove from the display. The curve that is currently selected is highlighted by a color background. Now press the Enter key.

No.	File	Channel	Name	Color	Visible
Graph 0	C:\PROGRAMME\KRC\Trace\T...	Channel 0	v_soll_A1	No color	no
Graph 1	C:\PROGRAMME\KRC\Trace\T...	Channel 1	v_ist_A1	Green	yes


Info

Now close the information window again.

As you can see, your action has been registered. The deactivated curve is now no longer displayed.

3.8 Configuration

Before you can record something with the oscilloscope, you must first tell it WHAT and HOW it is to record. For this purpose, the oscilloscope function offers a range of configuration options.



A window is opened on the display. Data which characterize the trace in greater detail must be entered here.

Name of recording: **TRACE**

Length of recording (sec): **12**

Triggermoment (in %): **0**

Triggervalue 1: **100**

Triggervalue 2: **25**

#T_END Trace - status: **inactive**

1. DSE

Triggervariable: **noEA**

Input / output area: **inactive**


Trigger on start of movement

Values to record

Channelname	Chan...	Recor...
Command_Value	1	no
Actual_Value	1	no
Following_Error	1	no
Comm_Velocity	1	yes
Actual_Velocity	1	yes

25.000

The various **input boxes** can be selected using the "↓" and "↑" arrow keys. Then enter the desired values by means of the keyboard or numeric keypad.



Use the “←” and “→” arrow keys in **selection boxes**, which can be identified by the arrow symbol on the right, to select from the options offered.



If the “Values to record” box is activated (dark blue highlight), you can also change the channel name by pressing the “←” and “→” arrow keys. A channel name is activated or deactivated by repeatedly pressing the “Enter” key.

3.8.1 Name of recording

A file name under which the trace will be saved later can be defined here. Do not use more than seven characters because a further digit is added to the file name by the system in order to distinguish different types of trace.



These trace files can be found with the extension TRC in the directory C: \PROGRAM FILES\KRC\TRACE.

3.8.2 Length of recording


Please enter an integer value here specifying the length of the trace in seconds.



The cycle rate for recording DSE data is 2 ms. 500 data sets are therefore generated in one second. Please take this volume of data into account when programming the length of the trace.



3.8.3 Trigger moment

Specify the position in time of the trace in relation to the trigger time in this field. The value between 0% and 100% that is entered refers to the programmed trace length.



3.8.4 Trigger value1/Trigger value2

In the field "Trigger value1", enter the value that triggers the trace when it is undershot. In the field "Trigger value2", enter the value that triggers the trace when it is exceeded. This trigger value is of the data type DOUBLE.



Information about data types can be found in the [KRL Reference Guide].

3.8.5 Trace status

The current working status of the oscilloscope can be seen in this box.

Trace status	Meaning
#T_WAIT	Trace is started and is waiting for the trigger condition. All of the data before the trace is triggered are recorded.
#TRIGGERED	Trace is triggered and runs for as long as specified in the boxes "Length of recording (sec)" and "Triggermoment".
#T_END	Trace is finished, the data are saved on the hard disk.

3.8.6 DSE (Digital Servoelectronics)

You can select here whether you want to record data from the first DSE or from the second DSE. If you do not want to record any DSE data and only want to monitor the inputs and outputs of the controller, please select here the option "No DSE data".



Files containing the traces of DSE data are identified by the end digit "1".

The cycle rate for recording DSE data is 2 ms. 500 data sets are therefore generated per second.



3.8.7 Trigger variable

If you only want to record DSE data, please select here the option "No I/O".

Otherwise, you can distinguish the previous selection made under "Input / output area" more clearly here. From the 32 inputs and outputs that you selected previously, you can now have the first or the last 16 inputs or outputs monitored for the occurrence of the trigger condition.



Files containing data about the status of inputs and outputs are identified by the end digit 3.
The cycle rate for recording the activities of inputs and outputs is 12 ms. About 85 data sets are therefore generated per second.

3.8.8 Input / output area

If you only want to record DSE data, please select here the option "inactive".

The inputs and outputs are each combined into 32-bit groups. You can select here, for example, whether inputs and outputs 1 to 32 or inputs and outputs 33 to 64, etc., are to be recorded.

3.8.9 Trigger conditions

In this field, select the condition which, when met, will trigger recording.

Start by user, recording until buffer is full
The recording must be initiated manually with the softkey "Start". It continues until the set recording length has been reached.
Cyclic recording, until user stops
Recording is carried out for the time specified in "Length of recording" <u>before termination</u> with the softkey "Stop" is recorded.
Trigger on appearance of error
Recording is carried out for the time specified in "Length of recording" around the appearance of an error that stops the robot system. The location of this period of time depends on the value set as the trigger moment.
Trigger on start of movement
The recording starts whenever the beginning of a motion instruction is reached or a motion instruction is being executed. It continues until the set recording length has been reached. The location of this recording time depends on the value set as the trigger moment.
Trigger on signal <> value 1
The recording starts as soon as the value of the selected trigger variable is not equal to the value specified as trigger value 1. It continues until the set recording length has been reached. The location of this recording time depends on the value set as the trigger moment.
Trigger on trigger variable = trigger value 1
The recording starts as soon as the value of the selected trigger variable is equal to the value specified as trigger value 1. It continues until the set recording length has been reached. The location of this recording time depends on the value set as the trigger moment.

Trigger on trigger variable < trigger value 1
The recording starts as soon as the value of the selected trigger variable is less than the value specified as trigger value 1. It continues until the set recording length has been reached. The location of this recording time depends on the value set as the trigger moment.
Trigger on trigger variable > trigger value 1
The recording starts as soon as the value of the selected trigger variable is greater than the value specified as trigger value 1. It continues until the set recording length has been reached. The location of this recording time depends on the value set as the trigger moment.
Trigger on trigger value 1 < trigger variable < trigger value 2
The recording starts as soon as the value of the selected trigger variable is greater than the value specified as trigger value 1 <u>and</u> less than the value specified as trigger value 2. It continues until the set recording length has been reached. The location of this recording time depends on the value set as the trigger moment.
Trigger on clearing filter
This option is intended for our service personnel only.
Trigger variable AND trigger value 1 = trigger value 2
The recording starts as soon as the result of the logical ANDing of the two operands trigger variable / trigger value 1 is equal to trigger value 2. It continues until the set recording length has been reached. The location of this recording time depends on the value set as the trigger moment.
Trigger on DSE error
In this instance, recording is carried out for the time specified in "Length of recording" around the appearance of a hardware error that is signalled by the digital servo-electronics (e.g. "Command value out of range", "Cabinet temperature too high"). The location of this period of time depends on the value set as the trigger moment.

3.9 Values to record

The data from the DSE that are to be recorded are defined in this selection box.

Values to record	Meaning
Command Value *1)	Command value from the interpolator per position control cycle
Actual Value *1)	Actual value per position control cycle
Following Error *1)	Difference between command position and actual position
Command Velocity *1)	At the position controller output
Actual Velocity *1)	Motor speed
Current *1)	At the speed controller output
Motor temperature *1)	In increments
Resolver *1)	Encoder position
Test_IN_1	This option is intended for our service personnel only.
Test_IN_2	This option is intended for our service personnel only.
Bus_Voltage-PM 1	Power module 1
Bus_Voltage-PM2	Power module 2
*1) For each of the channels 1...8	

After selecting the variable that is to be recorded, the trace can be selected or deselected by repeatedly pressing the Enter key.

3.9.1 Softkeys

Save	The current configuration is saved by pressing the softkey "Save". It is then available for every further recording process.
Start	Recording is started by pressing the softkey "Start". It begins as soon as the selected trigger condition is met.
Trigger	Recording is started manually irrespective of the selected trigger condition by pressing the softkey "Trigger".
Stop	Recording is stopped by pressing the softkey "Stop". All of the data that have been recorded thus far are saved.
Monitor	The softkey "Monitor" has the same function as the menu key "Monitor" followed by the submenu "Diagnosis" and the option "Monitor". Further information can be found in Section 3.1.
Close	The window for configuring the oscilloscope is closed by pressing the softkey "Close". The entered values will <u>not</u> be saved.

3.9.2 Examples of traces

As the oscilloscope function with all the configuration and display options is somewhat complex, we want to introduce you to the use of this tool with the aid of a small example.



Example 1

The:

- the command speed of the drive of axis 1,
- the actual speed of the drive of axis 1,
- the torque of the drive of axis 1
- the status of outputs 1 to 16

are to be monitored.

Create a motion program which, amongst other things, moves axis 1 and operates outputs 1 to 16.

Press the menu key "Monitor" and select the option "Diagnosis". In the submenu which opens, please confirm the selection "Oscilloscope". Now select "Configuration".

Please leave the default name "TRACE" as it is.

Enter the value "12" in the field "Length of recording (sec)".

Enter the value "0" in the field "Trigger moment".

Also enter the value "0" in the fields "Trigger value1" and "Trigger value2".

Select the first DSE.

Select "\$IN[1..32], \$OUT[1..32]" in the field "Input / output area".

Specify "Trigger on start of movement" as the trigger condition.

Switch on the trace for "Command velocity channel 1", "Actual velocity channel 1" and "Torque channel 1" in the field "Values to record".

Press the softkey "Save".

Now start the motion program and then press the softkey "Start".

The command speed, the actual speed and the torque of the drive of axis 1 and the statuses of inputs 1 to 32 will now be recorded and saved until the data buffer is full and the trace status changes to #T-END. The files are called TRACE1.trc and TRACE3.trc.



Example 2

The signals of inputs and outputs 1 to 32 are to be recorded as soon as input 3 takes on the state "TRUE".

- G Enter a concise name of your choice under "Name of recording". Make sure that the length of this name does not exceed seven characters because a digit will later be added by the system in order to distinguish different types of trace.
- G Enter the value 12 in the box "Length of recording". The recording length will then be 12 seconds.
- G Enter the value 0 in the box "Triggermoment". The data will then be recorded from the moment input 3 takes on the state "TRUE".
- G Enter the value 4 for input 3 in the boxes "Triggervalue 1" and "Triggervalue 2".



Why the value 4?

Input	5	4	3	2	1
Signal			X		
Bit	4	3	2	1	0
Binary	0	0	1	0	0

The binary value 100 corresponds to the decimal value 4.



The decimal value corresponding to an output or input is determined by raising the bit number to the power of 2.

Select "Trigger variable AND trigger value 1 = trigger value 2" as the trigger condition.



Why this trigger condition?

Input	5	4	3	2	1
Signal	X	X	X		
Bit	4	3	2	1	0
Binary	1	0	1	1	0

Binary	1	0	1	1	0	Value of the trigger variable; inputs 2, 3 and 5 set
--------	---	---	---	---	---	------------------------------------------------------

Logical ANDing with

Binary	0	0	1	0	0	Trigger value 1, decimal: 4
--------	---	---	---	---	---	-----------------------------

Result of logical operation:

Binary	0	0	1	0	0	Trigger value 2, decimal: 4
--------	---	---	---	---	---	-----------------------------

- G Select "No DSE data" in the DSE data box.
- G Select the first input group (\$IN[x..x+15]) as the trigger variable.
- G Select the first 32-bit group (\$IN[1..32], \$OUT[1..32]) in the box "Input / output area".
- G Now save the configuration by pressing the softkey "Save", then activate the data recording process by means of the softkey "Start".

Input 3 will now be monitored for occurrence of the trigger condition. The message "#T_WAIT" is displayed in the box "Trace-status". This message changes to "#TRIGGERED" as soon as the trigger condition is fulfilled. The signals of inputs and outputs 1 to 32 will be recorded for 12 seconds from this moment onwards.



Example 3

A robot program branches to various subprograms depending on how the PLC sets specific signals. In a certain, unknown situation, the program branches to the subprogram "SP55.SRC", which is not desired in this configuration, however.

For the purpose of checking the I/O communication of the robot program with the PLC in this situation, an unassigned output (e.g. output 32) can be set in the subprogram SP55 and reset again on quitting the subprogram.

A trace can now be triggered at this output and the recorded sequence of events saved.

- G Enter a concise name of your choice under "Name of recording". Make sure that the length of this name does not exceed seven characters because a digit will later be added by the system in order to distinguish different types of trace.
- G Enter the value 10 in the box "Length of recording". The recording length will then be 10 seconds.
- G Enter the value 90 in the box "Triggermoment" as it is primarily the pre-event history that is of interest here. Recording of the data will then already start 90% of the recording length (9 seconds in this example) before the trigger moment. The recording will overlap the trigger moment by 1 second in this instance.
- G Enter the value 32768 for input 32 in the boxes "Triggervalue 1" and "Triggervalue 2".



Why the value 32768?

Input	34	33	32	31	30	...	19	18	17	16	15	14	...	3	2	1
Signal			X					
Data word	3		2		1											
Bit	1	0	15	14	13	...	2	1	0	15	14	13	...	2	1	0
Binary	0	0	1	0	0	...	0	0	0	0	0	0	...	0	0	0

The binary value 1000 0000 0000 0000 of data word 2 corresponds to the decimal value 32768.



The decimal value corresponding to an output or input is determined by raising the bit number to the power of 2.

Select "Trigger variable AND trigger value 1 = trigger value 2" as the trigger condition.



Why this trigger condition?

Input	34	33	32	31	30	...	19	18	17	16	15	14	...	3	2	1
Signal			X					
Bit	1	0	15	14	13	...	2	1	0	15	14	13	...	2	1	0
Binary	0	0	1	0	0	...	0	0	0	0	0	0	...	0	0	0

Binary	0	0	1	0	0	...	Value of trigger variable; inputs 2, 3 and 32 set									
--------	---	---	---	---	---	-----	---------------------------------------------------	--	--	--	--	--	--	--	--	--

Logical ANDing with

Binary	0	0	1	0	0	...	Trigger value 1, decimal: 32768									
--------	---	---	---	---	---	-----	---------------------------------	--	--	--	--	--	--	--	--	--

Result of logical operation:

Binary	0	0	1	0	0	...	Trigger value 2, decimal: 32768									
--------	---	---	---	---	---	-----	---------------------------------	--	--	--	--	--	--	--	--	--

- G Select "No DSE data" in the DSE data box.
- G Then select the last output group (\$OUT[x+16..x+31]) as the trigger variable.
- G Select the first 32-bit group (\$IN[1..32], \$OUT[1..32]) in the box "Input / output area".
- G Now save the configuration by pressing the softkey "Save", then activate the data recording process by means of the softkey "Start".

Output "17" will now be monitored with regard to this trigger condition. The message "#T_WAIT" is displayed in the box "Trace-status". This message changes to "#TRIGGERED" when the trigger condition is fulfilled. The signals of inputs and outputs 1 to 32 will be recorded for 10 seconds from this moment onwards.



Example 4

You discover that a robot program always stops at night because an error occurs in the I/O communication with the PLC. It cannot be determined whether this error is caused by the PLC program or the robot program since nothing is known about the incorrect communication at this point.

It is possible for the oscilloscope function to be started in the KRL robot program before this situation and to be ended after it. The data are overwritten every time the program is correctly executed. If the motion program is interrupted by an error message, however, the last trace is saved and the error can be analyzed with the aid of the recorded data.

- G Enter a concise name of your choice under "Name of recording". Make sure that the length of this name does not exceed seven characters.
- G Enter a value in the box "Length of recording" taking into account the time for communication between the robot and the PLC.
- G Enter the value 0 in the boxes "Triggermoment", "Triggervalue 1" and "Triggervalue 2".
- G Select the option "Start by user, recording until buffer is full" as the trigger condition.
- G Select "No DSE data" in the DSE data box.
- G Then select "No E/A" as the trigger variable.
- G Select the first 32-bit group (\$IN[1..32], \$OUT[1..32]) in the box "Input / output area".
- G Now save the configuration by means of the softkey "Save", and quit the oscilloscope function by pressing the softkey "Close".
- G Insert the following lines into the KRL program before the selected program section in order to start the trace:

```
$TRACE. MDE=#T_START
REPEAT
UNTIL $TRACE. STATE == #T_WAIT
```

Insert the following lines into the KRL program after the selected program section in order to stop the trace:

```
$TRACE. MDE=#T_END
REPEAT
UNTIL $TRACE. STATE == #T_END
```



These changes can only be made at the expert level.

As soon as the error has been located, these instructions must be removed from the program again.

